

Nr.	Getriebe	Ausgangs- welle	Hohlwelle	einstufig	zweistufig	max. zul. Dreh- moment [Nm] von - bis	Getriebedrehzahl (Upm) Motordrehzahl 1400 bzw. 2800 Upm
1	SN 5 FL	√		√		5-15	14-1120
2	SN 5 FR	√		√		5-15	14-1120
3	SN 18	√		√		5-15	14-1120
4	SN 14	√		√		5-15	14-1120
5	SN 3 F	√		√		11-17	19-560
6	SN 3 FL	√		√		11-17	19-560
7	SN 9 F	√		√		23-36	18-207
8	SN 8 F	√		√		54-113	19-295
9	SN 10 F	√		√		121-230	19-224
10	SN 4 F	√			√	6-7	0,9-224
11	SN 6 F	√			√	11-15	0,9-56
12	SN 2 F	√			√	16-20	0,4-112
13	SN 12 F	√			√	25	2,8-224
14	SN 12 FX	√			√	23-35	3,2-253
15	SN 11 F	√			√	35-36	0,6-56
16	SN 13 F	√			√	31-50	2,4-190
17	SN 7 F	√			√	72-113	0,6-40
18	SN 19 F	√			√	111-120	3,5-84
19	SN 5 FLH		√	√		5-15	14-1120
20	SN 5 FRH		√	√		5-15	14-1120
21	SN 18 H		√	√		12-13	25-400
22	SN 14 H		√	√		11-17	19-560
23	SN 3 VH		√	√		11-17	19-560
24	SN 3 BHFL		√	√		11-17	19-560
25	SN 3 FH		√	√		11-17	19-560
26	SN 3 FLH		√	√		11-17	19-560
27	SN 9 BFH		√	√		23-36	18-207
28	SN 9 FH		√	√		23-36	18-207
29	SN 8 BFH		√	√		54-113	19-295
30	SN 8 FH		√	√		54-113	19-295
31	SN 8 DSH		√	√		54-113	19-295
32	SN 10 BFH		√	√		121-230	19-224
33	SN 10 FH		√	√		121-230	19-224
34	SN 6 FH		√		√	11-15	0,9-56
35	SN 12 FH		√		√	25	2,8-224
36	SN 12 FHX		√		√	23-35	3,2-253
37	SN 13 FH		√		√	62-70	3,3-140
38	SN 19 FH		√		√	111-120	3,5-84